

RMP200 Kits

TECHNICAL DATA

Rack Mount Kit for One Receiver

RMP200-1 Kit



Kit includes:

- | | |
|----------------|--|
| 1 - 25877 | Angle Bracket (rack ear) |
| 1 - RMP200-1M0 | Half Rack Mount (triangular support bracket) |
| 2 - 28735 | 10-32 x 1/2" Phillips Head Machine Screws |
| 3 - 28736 | 10-32 x 3/4" Phillips Head Machine Screws |

Step 1

Turn the receiver and support bracket upside down and arrange as shown in the photo below. Mount the bracket with 3ea. 10 - 32 x 3/4" Phillips head machine screws.



The receiver is now ready to be installed in the rack.

Step 2

Attach the rack ear to the right side of the receiver. Mount with 2ea. 10 - 32 x 1/2" Phillips head machine screws.



Rio Rancho, NM, USA
www.lectrosonics.com

Rack Mount Kit for Two Receivers



Kit includes:

- 2 - 25877
- 1 - 25878
- 1 - 25879
- 4 - 28735
- 2 - 28736

Angle Bracket (rack ears)

Block (narrow)

Block (wide)

10-32 x 1/2" Phillips head machine screws

10-32 x 13/16" Phillips head machine screws

Step 1

Remove the original corner blocks (3 holes) from the front and rear to install replacement blocks. (save the four small screws, you will need them to install the new blocks)



Front of right hand receiver

Step 3

Attach the wide replacement block to rear of receiver using the screws removed in Step 1.

Use the 10-32 x 13/16" Phillips head machine screw to mount the two units together.



Rear of left hand receiver



Step 4

Attach rack ears to the right and left sides of the receivers, with the 10-32 x 1/2" Phillips head machine screws provided in kit.

The units are now ready to be installed in the rack.



Step 2

Attach the narrow replacement block (single hole) to front of receiver using the small screws removed in Step 1.

Use the 10-32 x 13/16" Phillips head machine screw to mount the two units together.

